BATTERY SYSTEMS / MANUFACTURER-STATED RATINGS

WattCycle 12V 100Ah Camper Underseat LiFePO4 Battery with Self-heating

12.8 V nominal • 100 Ah • 1280 Wh • LiFePO4 chemistry

12.8 V	100 Ah	1280 Wh
NOMINAL VOLTAGE	RATED CAPACITY	RATED ENERGY

Electrical and BMS limits

BMS continuous current rating	100 A
Maximum continuous discharge current	100 A
Maximum charge current	100 A
Charge voltage	14.4 V

Features and physical data

PVShop model	PVS-BAT-7A4E82F92A
Cell chemistry	LiFePO4
Product features	Bluetooth monitoring, self-heating, low-temperature charge protection
Dimensions (L × W × H)	L354 x W176 x H187 mm
Weight	11.35 kg
Ingress protection	IP65
Maximum batteries in parallel	4 batteries
Maximum batteries in series	4 batteries

Selection note

Match nominal voltage, current limits, charge profile, physical size and environmental rating to the complete installation. Cable, fuse, busbar and disconnect ratings must follow the documented continuous current and local electrical rules.

DETAILED SPECIFICATION RECORD

WattCycle 12V 100Ah Camper Underseat LiFePO4 Battery with Self-heating

Additional manufacturer ratings

Dimensions (L × W × H)	L354 x W176 x H187 mm
Terminals	M8 Bolts
Warranty	5 Years (Register the warranty for a 2-year extension)
Certifications	CE-EMC, RoHS, FCC-SDOC, CE-Battery, UN38.3
Monthly Self Discharge	≤3%/Month
Series / parallel configuration	Max. 4 in Parallel, Max. 4 in Series
Charge Cut-Off Voltage	14,4±0,2V
Charging Temperature	0℃-55℃
Discharging Temperature	-20℃-60℃
Storage Temperature	0℃-45℃

Evidence and revision control

PVShop model	PVS-BAT-7A4E82F92A
Manufacturer record	Current manufacturer product page and available manufacturer documents
Evidence review date	12 September 2026
Specification policy	Published values reproduced without performance estimates; undocumented fields remain blank

SOURCE STATUS Manufacturer-stated; not independently laboratory tested by PVShop.

The source was reviewed on 12 September 2026. Ratings omitted by the manufacturer are intentionally left blank. Manufacturer pages can change; use the issue date and PVShop model above when requesting technical support.

Safety: follow the installation manual. Do not short-circuit, crush, puncture, dismantle or expose the battery to fire. Do not charge outside the published temperature range. Use a compatible CC/CV LiFePO4 charger and suitable over-current protection. A deep-cycle model is not a starting battery unless the manufacturer explicitly provides a starting-current rating.